WIRELESS N

How to Setup EWAN for NBN connections



This document will detail how to setup EWAN for NBN connections

						_ 0 ×
← → http://192.168.1.1/	login.html	Q	👻 🗟 🧭 ADSL Router	×		n ★ ☆
	Product Page: DSL-2	2750B		Fi	mware Version: AU_3.01	
	D-Lit	ık				
		LOGIN				
		Welcome to DSL-2750B Web Management				
		Username :	admin 🗸			
		Password :	Demonsher my lanin infe			
			kemember my login inio.			
			Login			
	WIRELESS					
		Copyright @	0 2008-2011 D-Link Systems, Inc.			

1. Open your Internet Browser and in the URL field type in http://192.168.1.1.

2. Type in the default Username and Password then click on the Log In button. These values are provided below:

Username: admin

Password: admin

3. You should now be present with the DSL-2750B Revision T1 Web Configuration:

← → http://192.168.1.1	/index.html		Q + ₿(🖄 🧀 D-Link ADSL Router	×		<u> </u>
	Product Page: DSL-275	⁶⁰⁸			⊧ <u>Site Map</u>	^	
	DSL-2750B	SETUP	ADVANCED	MAINTENANCE	STATUS	HELP	
	Ward Internet Setup Wineless Connection Local Network IPv6 Local Network Time and Date Logout UBURELESS	SETTING UP YOU There are two ways to Connection Setup Wiz Please make sure you INTERNET CONN You can use this wiza Internet. You will be p up and running. Click Note: Before launchir the Quick Installation	SETTING UP YOUR INTERNET There are two ways to set up your Internet connect Connection Setup Wizard or you can manually confir Please make sure you have your ISP's connection set INTERNET CONNECTION WIZARD You can use this wizard for assistance and quick con Internet. You will be presented with step-by-step in up and running. Click the button below to begin. Setup W Note: Before launching the wizard, please ensure y the Quick Installation Guide included with the routed		b-based Internet manual setup. Ink Router to the your Internet connectio	Helpful Hints First time users are recommended to run the Setup Wizard. Click the Setup Wizard Litton and you will be guided step by step through the process of setting up your ADSL connection. If you consider yourself an advanced user or have configured a router before, click Setup bo input all the settings manually. More	
			Copyright © 2008-2	011 D-Link Systems, Inc.			×

4. Please click on [SETUP] > [Internet Setup], select [ETH WAN] then click on [Add] button

C A Mttp://19216811/	index html		0 - 8	🖒 🤇 D. Link ADSL Rau	ter X		
	Product Page: DSL-275	ob K	, , , , , , , , , , , , , , , , , , ,	U U LINE ADSL ROU	Site Map	Firmware Version: AU_3.01	^
	Wizard Wizard Wireless Connection Local Network IPv6 Local Network Time and Date Logout	SETUP INTERNET SET Choose "Add", "Ed If you want to cha WAN Services type WAN SETUP VPI/VCI	ADVANCED UP it", or "Delete" to configure V nge WAN services type, Pleas E ETH WAN DSL VLAN Mux Service	MAINTENANCE /AN Interfaces. A maximu e select ETH or DSL Name Protocol	STATUS	HELP igured.	
	WIRELESS						
			Copyright © 2008-	2011 D-Link Systems, Inc.			~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~

5. Select [MAC Encapsulation Routing (MER)] then click on [Next] button at the bottom of the page.

C 🏈 🤌 http://192.168.1.1/index.html	© 5⊠ + Q	D-Link ADSL Router ×		<u>+</u> ★ ☆
Product Page: I	5L-2750B	Firmware Version: AU_3.01	^	
D-L	nk			
DSL-2750B	SETUP ADVANCED M	MAINTENANCE STATUS	HELP	
Wizard	INTERNET SETUP		Helpful Hints	
Internet Setup	Wide Area Network (WAN) Service Setup		When configuring the router to access the	
Wireless Connect		Internet, be sure to choose the correct		
Local Network		Connection Type from the list below.		
Time and Date	Protocol:	MAC Encapsulation Routing (MER) 🗸	Please take care when	
Logout	Enable Multiple Vian Over One Connection:	_1	username and nassword as these are	
	802.10 VLAN ID [0-4094];	-1	case sensitive. The majority of connection	
			issues are caused by incorrect username or	
	WAN IP SETTINGS		password combinations.	
			More	
	IPV4 Setting			
	Obtain an IP address automatically			
	O Use the following IP address:			
	WAN IP Address:			
	WAN Subnet Mask:			
	Default Gateway:			Ý

←	P → 🗟 C 💋 D-Link ADSL Router ×	↑ ★ ‡
	Secondary DNS server: IPV6 Setting Enable IPv6 for this service.	^
	 Obtain an IPv6 address automatically: Request IPv6 Address: Request Prefix Delegation: 	
	Use the following Static IPv6 address: Wan IPv6 Address: Wan IPv6 Subnet Prefix Length: Wan Gateway IPv6 Address: Primary IPv6 Dns: Secondary IPv6 Dns:	
	NETWORK ADDRESS TRANSLATION SETTINGS Enable NAT: Enable Firewall: Enable IGMP Multicast: Enable MLD Proxy: Service Name: mer_eth4 Next Cancel	
		~

5. Click on **[Apply]** button at the bottom of the page to save the changes.

	-						
(→) @ http://19	2.168.1.1/index.html		<u>م</u> - 2	C 🥝 D-Link ADSL Router	×		<u>+</u> ★ ☆
	Product Page: DSL-275	0B			▶ <u>Site Map</u> Fi	irmware Version: AU_3.01	^
	D-Lin	k					
	DSL-2750B	SETUP	ADVANCED	MAINTENANCE	STATUS	HELP	
	Wizard	WAN					
	Internet Setup	Make sure that the se	ttings below match the set	tings provided by your ISP.			
	Wireless Connection	Click "Apply" to save a	and activate these settings	. Click "Back" to make any m	odifications.		
	IPv6 Local Network	SETUP - SUMMARY					
	Time and Date						
	Logout	ETH port:		eth4			
		Connection Type:		IPoE			
		Service Name:		mer_eth4			
		IP Address:		Not Applicable			
		Service State:		Enabled			
		NAT:		Enabled			
		Firewall:		Enabled			
		IGMP Multicast:		Enabled			
			Back	Apply			,