

DIR-457U VirginBroadband - 3G/4G Settings

Open an Internet Browser and in the address bar, type in <http://192.168.0.1>



The default username is admin and the password is left blank.

A screenshot of the router's login page. The page has an orange header with the word "LOGIN" in white. Below the header, it says "Log in to the router:". There are two input fields: "User Name" with "admin" entered, and "Password" which is empty. A "Log In" button is to the right of the password field.

Select [Manual Internet Connection Setup] under [SETUP] > [Internet Setup]

A screenshot of the D-Link router's configuration page. The top has the "D-Link" logo. Below it is a navigation menu with "DIR-457" and "SETUP" (highlighted with a red box), "ADVANCED", "MAINTENANCE", "STATUS", and "HELP". On the left is a sidebar with "Internet Setup" (highlighted with a red box), "Wireless Setup", "LAN Setup", "Time and Date", "Logout", and a "Reboot" button. The main content area is titled "INTERNET CONNECTION" and contains instructions for using the "Internet Connection Setup Wizard" and "Manual Internet Connection Options". The "Manual Internet Connection Setup" button is highlighted with a red box. On the right is a "Helpful Hints.." section with two bullet points.

- Select [Manual] for Dial-Up Profile
- Select Country [Australia]
- ISP [Optus]
- Username enter [guest]
- Password enter [guest]
- Authentication Protocol select [PAP only]
- APN enter [virginbroadband]
- Reconnect Mode select [Always-on]

Click on [Save Settings] button to apply the changes.

WWAN INTERNET SERVICE PROVIDER SETUP

Enter the information provided by your Internet Service Provider (ISP).

Mode :

Country :

ISP :

PIN : (optional)

User Name : (optional)

Password : (optional)

Dial Number :

Authentication Protocol :

APN : (optional)

Reconnect Mode : Always-on Connect-on demand Manual

Maximum Idle Time : (minutes,0=infinite)

DNS Mode : Receive DNS from ISP Enter DNS Manually

Primary DNS Address :

Secondary DNS Address : (optional)