



## KVM Switch for 4 PCs

The DKVM-4K 4-port KVM switch is a cost-effective KVM solution for office users and business. This switch allows you to easily control 4 different PCs from a single set of keyboard, mouse, and VGA monitor. The switch provides many easy to use features and is perfect for MIS, network administrators and business users.

### Cost-effective for PC Users

If you need to control several computers at the same time (such as in a computer room), the DKVM-4K saves you the money and space by allowing you to control your the computers from a set of keyboard, monitor and mouse. You may have a better, bigger monitor and want to connect all 4 PCs to it, the DKVM-4K allows you to do this.

### High Performance and Easy Management of Port Traffic/Server Control

The DKVM-4K allows you to manage port traffic and boot up the attached PCs. A control button located on the top of

the DKVM-4K gives you one touch access to your attached PCs. Featuring hot-plug, auto-scan, keyboard hot-keys and audible feedback, this switch makes it simple to manage all of your computers.

### Status Save and High Resolution Support

The DKVM-4K supports VGA, SVGA, and MultiSync monitors at up to 2048 x 1536 resolution. Support for Microsoft IntelliMouse is provided.

## Features

- Bus-power support (no external power connection required)
- Allows control of 4 PS/2 style computers from a set of single keyboard, mouse, monitor
- Keyboard and mouse emulation for error-free boot-up
- VGA, SVGA and Multisync monitor resolution 2048 x 1536 support
- Microsoft IntelliMouse and Microsoft IntelliMouse Explorer support
- PS/2 style keyboard, mouse support
- Switch among the 4 PCs via "Select" push button and Hot-Key commands
- Auto-scan mode for convenience automatic switching (Scan boot up PCs)
- Audible feedback when switching
- 4 LED indicators for each connected computer
- Automatic recall of CAPS LOCK, NUM LOCK and SCROLL LOCK Key's status for each computer
- Uses inexpensive, commonly available cables

# DKVM-4K

## Technical Specifications

## KVM Switch

### Console Connectors (connect to keyboard, mouse, monitor)

- Keyboard connector: mini DIN-6 PIN female
- Mouse connector: mini DIN-6 PIN female
- Monitor connector: HD 15 PIN female

### KVM Connectors (connect to computers)

- 4 keyboard connectors: mini DIN-6 PIN female
- 4 mouse connectors: mini DIN-6 PIN female
- 4 monitor connectors: HD 15 PIN female

### Diagnostic LEDs

- 4 port LEDs for 4 connected Purchase
- A lit (green) status indicates the port is active

### PC Selection (Manually switching back and forth among the PCs)

- Through push button
- Through Hot Key
- Switching confirmation: buzzer sound

## Physical & Environmental

### Power Input

From PC's PS2 port, no power adapter required

### Dimensions

178 x 105 x 30.5 mm (KVM switch only)

### Operating Temperature

0° to 50 °C

### Storage Temperature

-10° to 60 °C

### Humidity

5% to 90%

### Emission (EMI)

- FCC Class B
- CE Class B
- C-Tick

### Box Includes

- 4-port KVM switch
- 2 sets of 1.8 m (6 ft) KVM cables
- Quick Installation Guide



ACN 052 202 838

## Ordering Information

**DKVM-4K** 4-port mini KVM switch

### Optional Cable Set

**DKVM-CB** Set of 1.8 meter (6 ft) KVM cables

# D-Link®

Specifications subject to change without prior notice.  
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

### U.S.A

### Canada

### Europe

### Germany

### France

### Benelux

### Italy

### Iberia

### Sweden

### Norway

### Denmark

### Finland

### Singapore

### Australia

### Japan

### China

### India

### Middle East (Dubai)

### Turkey

### Egypt

### Israel

### Chile

### Brasil

### South Africa

### Russia

### Taiwan

### D-Link Corp.

TEL: 1-714-885-6000

TEL: 1-905-8295033

TEL: 44-20-8731-5555

TEL: 49-6196-77990

TEL: 33-1-30238688

TEL: 31-10-282-1445

TEL: 39-2-2900-0676

TEL: 34-93-4090770

TEL: 46-(0)8564-61900

TEL: 47-22-309075

TEL: 45-43-969040

TEL: 358-9-2707-5080

TEL: 65-6774-6233

TEL: 61-2-8899-1800

TEL: 81-3-5434-9678

TEL: 86-10-8518-2533

TEL: 91-022-652-6696

TEL: 9714-8834234

TEL: 90-212-335-2553

TEL: 202-414-4295

TEL: 972-9-9715700

TEL: 56-2-232-3185

TEL: 55-11-55039320

TEL: 27(0)1266-52186

TEL: 7-095-744-0099

TEL: 886-2-2910-2626

TEL: 886-2-2916-1600

FAX: 1-866-743-4905

FAX: 1-905-8295223

FAX: 44-20-8731-5511

FAX: 49-6196-7799300

FAX: 33-1-30238689

FAX: 31-10-282-1331

FAX: 39-2-2900-1723

FAX: 34-93-4910795

FAX: 46-(0)8564-61901

FAX: 47-22-309085

FAX: 45-43-424347

FAX: 358-9-2707-5081

FAX: 65-6774-6322

FAX: 61-2-8899-1868

FAX: 81-3-5434-9868

FAX: 86-10-8518-2250

FAX: 91-022-652-8914

FAX: 9714-8834394

FAX: 90-212-335-2500

FAX: 202-415-6704

FAX: 972-9-9715601

FAX: 56-2-232-0923

FAX: 55-11-55039321

FAX: 27(0)1266-52186

FAX: 7-095-744-0099#350

FAX: 886-2-2910-1515

FAX: 886-2-2914-6299



RECYCLABLE  
Rev. 01 (Dec. 2003)