

How to enable Wi-Fi security in your modem router

This document details how to set security on your modem router's wireless network

Step 1. Open your Internet browser e.g. Internet Explorer, Firefox, Chrome, Safari, etc. and enter the IP address of your D-Link modem in the **address bar**: http://10.1.1.1



Step 2. When prompted type in the Username and Password, then click on the “OK” button.
If you have not changed the password for the modem administration, the factory settings are:

Username: admin

Password: admin



If you cannot recall the password you assigned to your modem you will need to reset the modem to factory defaults by pressing the reset button for 10 seconds. Please note that this will revert all the settings in the modem to factory settings and you will have to reconfigure it with your Internet settings and Wireless security. Make sure you have your Internet account details (given by your Internet Provider) handy.

Step 3. After logging in you will be presented with the modem's configuration pages. Please click on **Home** tab and then select **Wireless**.



Step 4. You can change your Wi-Fi network name to something you can easily identify (SSID Field). For best security level select “WPA” and “WPA2”. Select the [Pre-Shared Key] field type the Wi-Fi password you want to use. (All devices connecting to your Wi-Fi for the first time would have to enter this password)

Click on Apply.



Step 5. To save the new settings into the modem's memory click on the [Tools] tab and then on [System]. Click on the "Save and Reboot" button.

The screenshot displays the D-Link DSL-G604T Web Management Interface. At the top, there is a navigation bar with tabs for Home, Advanced, Tools, Status, and Help. The 'Tools' tab is highlighted with a red circle. On the left side, there is a vertical menu with buttons for Admin, Time, Remote Log, System, Firmware, Miscellaneous, Test, and Logout. The 'System' button is also highlighted with a red circle. The main content area is titled 'System Settings' and contains the following sections:

- System Settings**
The current system settings can be saved as a file onto the local hard drive.
- Save Settings To Local Hard Drive**
Save
- Load Settings From Local Hard Drive**
Browse...
Load
- Note: The system has to be restarted after the configuration is restored.
- Save Settings and Reboot the System.**
Save and Reboot
- Restore To Factory Default Settings**
Restore
- Force the DSL-G604T Wireless LAN to restart.**
Restart AP