DVG-G1402S VoIP Configuration With GOTalk

Log into the DVG-G1402S: open your Internet Explorer and type in the IP address of the unit (by default it is 192.168.15.1). Select VoIP menu. You only need to modify "Server Configuration" and "User Agent" settings.

Provisioning, STUN, Peer-to-Peer, Telephony, and Misc. options can be left at their default settings.



Specify the following under Server Configuration:

Register Expiration	m	3600	S	ec
Session Expires		180	s	ec
Min-SE		180	sec	
Session Expires I	Refresher	uac 🗸	1	
Codec Priority &	Packet Interva	1		
G.711a-law	3rd	~	20	🚩 ms
G.711u-law	2nd	~	20	✓ ms
G.723.1	no-use	*	30	🗙 ms
G.729a	1st	~	20	Y ms
G.726	no-use	~	20	🖌 ms
G.726	no-use	~	20	~ r

Click on the Apply button.

Enter your account settings under User Agent section:



Click on the Apply button.

After the configuration is done go to Tools tab on top and select the Reboot option on the left. Click on the Reboot button.

Provisioning, STUN, Peer-to-Peer, Telephony, and Misc. options can be left at their default settings.

Cannot find server - Microso	ft Internet Explore ols Help	r provided by D-Lir	nk Australia			
Back - 🕥 - 🗙 💈	Search	🔶 Favorites 🚱	A • 🎍 🛒			
Address 🕘 http://192.168.15.1/htm	i/start.html	~ ~			✓ → Go	Links »
D-Link Building Networks for People			DVG-0 Wireless	S1402S VolP Router		
	Home	Advanced	Tools	Status	Help	
Wizard Wireless WAN LAN VolP	XML Provisionin Provisioning Fund Server URL Proxy Address Proxy Port Numb	g ction Disabled 	Apply Cancel H	Help		
DHCP Proxy DNS		ill			Internet	

Cannot find server - Microsoft Internet Explorer provided by D-Link Australia					- 🗆 🛛	
<u> </u>	<u>H</u> elp					-
🌀 Back 🝷 🕥 🕤 🔀 🔮	Search	📌 Favorites 🚱 🔗	- 🎍 🖻 🛛	<mark>,</mark> 🗱 🔏		
Address 🕘 http://192.168.15.1/html/start	.html				💙 🄁 Go	Links »
D-Link Building Networks for People	_	D	VG-G1 ireless Vo	1402S IP Router		
	Home	Advanced To	ools	Status	Help	
Wizard ST Wireless WAN LAN VolP	TUN Configura STUN Stat STUN Serv FQDN STUN Serv Address Stun Serve STUN Serv STUN Req STUN Req	e Disabled rer Disabled rer Disabled rer IP 0 . 0 . 0 . 0 . 0 . 0 . 0 . 0 . 0 . 0	0			
	C	NAT Type Detect	Back	k Apply Cancel	C) Help	
	Index	ויייום wiessage socket map ip/port	ip/poi	≺т≓ socket mappe rt	u	
	1	0.0.0.0:0	0.0.0.0	D:0		
	2	0.0.0.0 : 0	0.0.0.0	D:0		
e Done					🔮 Internet	■ ▼

🚳 Cannot find server - Micro	soft Internet Explore	r provided by D-Lii	nk Australia		
<u>File E</u> dit <u>V</u> iew F <u>a</u> vorites	Tools Help		~ ~		
🕞 Back 🝷 🐑 👻 📘	🛃 🏠 🔎 Search	🎌 Favorites 🤣	S- 🛸 🛙	2 📙 🛍 🍕	\$
Address 🕘 http://192.168.15.1/h	ntml/start.html				Go 🕴 Links 🎽
					^
D -Link			DVG-	G1402	S
Building Networks for People			Wireless	s VolP Rout	er
	Home	Advanced	Tools	Status	Help
Wizard	Peer to Peer				
	Index	1			
Wireless	Phone Number				
	User IP Address	@ 0	. 0 .	0	
WAN	Port	5060			
LAN			9 💟	1	
			Back Apply (Cancel Help	
VolP	SIP - Peer to Pe	er			
DHCP	Index Phone	e Number User IP	Address Port	Edit Delete	
	1	@ 0.0.0.0	5060	📝 📋	
Proxy DNS	2	@ 0.0.0.0	5060		
	3	@ 0.0.0.0	5060		
	4	@ 0.0.0.0	5060		
	5	@ 0.0.0.0	5060		
	6	@ 0.0.0.0	5060		
	7	@ 0.0.0.0	5060		
	8	@ 0.0.0.0	5060		
	9	@U.U.U @ 0.000	5060	⊡ ()	
<	10	@ 0.0.0.0	5060		>
🙆 Done					Internet



Cannot find server - Microsof	t Internet Explore	r provided by D-	Link Australia			
<u>File E</u> dit <u>V</u> iew F <u>a</u> vorites <u>T</u> oo	ols <u>H</u> elp					
🌍 Back 🝷 🕥 🕤 🞽 🛃	Search 🔎	☆ Favorites - 🎸	🗿 🛜 🍓		- 23	
Address 🕘 http://192.168.15.1/html	/start.html				💌 🄁 Go	Links »
						^
D-Link			DVC	C440	26	-
Building Networks for People			Wirolo	-GI4U	ZJ	
			wirele	SS VOIP RO	uter	
	Home	Advanced	Tools	Statu	is Helo	
			10000			
	MISC.					
Wizard	💿 Ring Cande	ence 🔘 Ring Def	ault Rule 🔘 Ri	ng Rule		
Window	ID Duration	On1 Off1	0n2 0ff2	On3 Off3	On4 Off4	
Wireless	1 1000000					
WAN	1 1800000	40 40				
	2 180000	40 80	0 0	0 0	0 0	
LAN	3 180000	16 8	16 80	0 0	0 0	
VoIP	4 180000	8 4	8 4	16 80	0 0	
	5 180000	8 4	16 4	8 80	0 0	
DHCP	6 180000	12 12	8 4	10 50	0 0	
	• 100000					
Proxy DNS	7 180000	20 60	0 0	0 0	0 0	
	8 180000	20 20	8 8	0 0	0 0	
				9 💟		
				васк Арр	ly Cancel Help	
E Done					Internet	





Status > Phone Call should show "Registered" under Registration State:

🕙 Cannot find server - Microsof	t Internet Explorer provid	led by D-Link Aus	tralia		
<u> </u>	ls <u>H</u> elp				.
🕒 Back 🔹 🐑 💌 🛃	Search 👷 Fav	vorites 🙆 🔗	• 🎍 🖻 📙 🇱 🍇	\$	
Address 🕘 http://192.168.15.1/html/	/start.html			💙 🄁 Go	Links »
	🔘 Network 💿 Phone	Call			
Device Info	Line 1 Status				
	Hook State Call State	OnHook StateNull	Registration State Tone State	Registered Null	
Stats Diagnostics	Message Warting Call 1 State Call 1 Direction Call 1 Mode Call 1 Codec Call 1 Packetization Call 1 Packetization Call 1 Hold Remote Call 1 Peer Name Call 1 Peer Name Call 1 Peer Number Call 1 Peer Name Call 1 Peer Name Call 1 Peer Name Call 1 Peer Name Call 1 Peer RTP Addr Call 1 Peer RTP Call 1 Packets Send Call 1 Decode Latency Call 1 Packets Lost Call 1 Packets Error	IDLE	Call 2 State Call 2 Direction Call 2 Mode Call 2 Codec Call 2 Packetization Call 2 T.38 Call 2 Hold Remote Call 2 Peer Name Call 2 Peer Name Call 2 Peer Namber Call 2 Peer Number Call 2 Peer Number Call 2 Peer RTP Addr Call 2 Peer RTP Addr	IDLE	
	Line 2 Status				
	Hook State Call State Message Waiting	OnHook StateNull	Registration State Tone State	Registered Null	
	Call 1 State Call 1 Direction Call 1 Mode Call 1 Mode Call 1 Packetization Call 1 T.38 Call 1 Hold Remote Call 1 Remote Hold Call 1 Peer Name Call 1 Peer Name Call 1 Peer Name Call 1 Peer RTP Addr Call 1 Peer RTP Addr Call 1 Mapped RTP Port Call 1 Mapped RTP Port Call 1 Duration Call 1 Packets Send Call 1 Packets Send Call 1 Bytes Recv Call 1 Bytes Recv Call 1 Dires Call 1 Decode Latency Call 1 Decode Latency Call 1 Packets Lost Call 1 Packets Lost Call 1 Packets Error	IDLE	Call 2 State Call 2 Direction Call 2 Mode Call 2 Codec Call 2 Packetization Call 2 T.38 Call 2 Hold Remote Call 2 Peer Name Call 2 Peer Number Call 2 Peer Number Call 2 Peer RTP Addr Call 2 Mapped RTP Port Call 2 Mapped RTP Port Call 2 Duration Call 2 Packets Send Call 2 Packets Recv Call 2 Bytes Recv Call 2 Bytes Recv Call 2 Bytes Recv Call 2 Directer Call 2 Decode Latency Call 2 Decode Latency Call 2 Packets Lost Call 2 Packets Error	IDLE	
A Done				Internet	

~ End of Document ~