





DI-724P+ Setup Wizard

Set Password

You may change the **admin** account password by entering in a new password. Click **Next** to continue.

Old Password

New Password

Reconfirm



Back



Cancel



Next



Exit



DI-724P+ Setup Wizard

Choose Time Zone

Select the appropriate time zone for your location and click **Next** to continue.

(GMT-08:00)Pacific Time (US & Canada)



Back



Cancel



Next



Exit



DI-724P+ Setup Wizard

Select Internet Connection Type (WAN)

Select the connection type to connect to your ISP. Click **Next** to continue.

☒ Dynamic IP Address

Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)

☐ Static IP Address

Choose this option to set static IP information provided to you by your ISP.

☐ PPP over Ethernet

Choose this option if your ISP uses PPPoE. (For most DSL users)

☐ Others

PPTP and BigPond Cable.



Back



Cancel



Next



Exit



DI-724P+ Setup Wizard

Set Dynamic IP Address

If your ISP require you to enter a specific host name or specific MAC address, please enter it in. The **Clone MAC Address** button is used to copy the MAC address of your Ethernet adapter to the DI-724P+. Click **Next** to continue.

Host Name (optional)

MAC Address 00 0D 88 B0 E0 D4



Back



Cancel



Next



Exit

DI-724P+ Setup Wizard

Set Wireless connection

Enter in the SSID name and Channel number to be used for the Wireless Access Point. Click **Next** to continue.

Network ID (SSID)	<input type="text" value="default"/>		
Channel	<input type="text" value="6"/>	WEP Encryption	<input type="text" value="Disable"/>
WEP Key	<input type="text"/>		



Back



Cancel



Next



Exit

DI-724P+ Setup Wizard

Setup Complete

The Setup Wizard has completed. Click on **Back** to modify changes or mistakes. Click **Restart** to save the current settings and reboot the DI-724P+.



Back



Restart



Exit

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home Advanced Tools Status Help

Wireless Settings

These are the wireless settings for the AP(Access Point) portion.

Network ID(SSID)

Channel

WEP ☐ Enabled ☒ Disabled

WEP Encryption

WEP Key 1

Key 2

Key 3

Key 4

802.1X Settings

☐ Enabled ☒ Disabled

Encryption Key Length Length ☐ 64 bits ☐ 128 bits ☐ 256 bits

Lifetime

RADIUS Server 1

IP

Port

Shared Secret

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home Advanced Tools Status Help

WAN Settings

Please select the appropriate option to connect to your ISP.

- ☒ Dynamic IP Address Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)
- ☐ Static IP Address Choose this option to set static IP information provided to you by your ISP.
- ☐ PPPoE Choose this option if your ISP uses PPPoE. (For most DSL users)
- ☐ Others PPTP and BigPond Cable.

Dynamic IP Address

Host Name (Optional)

MAC Address

Primary DNS Address

Secondary DNS Address

MTU

Auto-reconnect ☒ Enabled ☐ Disabled

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home Advanced Tools Status Help

WAN Settings

Please select the appropriate option to connect to your ISP.

- ☐ Dynamic IP Address Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)
- ☒ Static IP Address Choose this option to set static IP information provided to you by your ISP.
- ☐ PPPoE Choose this option if your ISP uses PPPoE. (For most DSL users)
- ☐ Others PPTP and BigPond Cable.

Static IP Address

IP Address

Subnet Mask

ISP Gateway Address

Primary DNS Address

Secondary DNS Address

MTU

Apply Cancel Help

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home Advanced Tools Status Help

WAN Settings

Please select the appropriate option to connect to your ISP.

- ☐ Dynamic IP Address Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)
- ☐ Static IP Address Choose this option to set static IP information provided to you by your ISP.
- ☒ PPPoE Choose this option if your ISP uses PPPoE. (For most DSL users)
- ☐ Others PPTP and BigPond Cable.

PPP over Ethernet

☒ Dynamic PPPoE ☐ Static PPPoE

User Name

Password

Retype Password

Service Name (Optional)

IP Address

Primary DNS Address

Secondary DNS Address

Maximum Idle Time Minutes

MTU

Auto-reconnect ☒ Enabled ☐ Disabled

Apply Cancel Help

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home **Advanced** **Tools** **Status** **Help**

WAN Settings

Please select the appropriate option to connect to your ISP.

- ☐ Dynamic IP Address Choose this option to obtain an IP address automatically from your ISP. (For most Cable modem users)
- ☐ Static IP Address Choose this option to set static IP information provided to you by your ISP.
- ☐ PPPoE Choose this option if your ISP uses PPPoE. (For most DSL users)
- ☒ Others PPTP and BigPond Cable.
 - ☐ PPTP (for Europe use only)
 - ☒ BigPond Cable (for Australia use only)

Dynamic IP Address for BigPond

User Name

Password

Retype Password

Login Server IP (Optional)

Auto-reconnect ☒ Enabled ☐ Disabled

Apply Cancel Help

DI-724P+



Wizard

Wireless

WAN

LAN

DHCP

Home **Advanced** **Tools** **Status** **Help**

LAN Settings

The IP address of the DI-724P+.

IP Address

Subnet Mask

Domain Name

Apply Cancel Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home Advanced Tools Status Help

Special Application

Special Application is used to run applications that require multiple connections.

☐ Enabled ☐ Disabled

Name

Trigger Port -

Trigger Type

Public Ports

Public Type

Apply Cancel Help

Special Application List

Name	Trigger	Public Port	
<input type="checkbox"/> Battle.net	6112	6112	
<input type="checkbox"/> Dialpad	7175	51200-51201,51210	
<input type="checkbox"/> ICU II	2019	2000-2038,2050-2051,2069,2085,3010-3030	
<input type="checkbox"/> MSN Gaming Zone	47624	2300-2400,28800-29000	
<input type="checkbox"/> PC-to-Phone	12053	12120,12122,24150-24220	
<input type="checkbox"/> Quick Time	554	6970-6999	
<input type="checkbox"/> DVC-1000 i2eye	1720	15328-15333	

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home Advanced Tools Status Help

Filter

Filters are used to allow or deny LAN users from accessing the Internet.

☒ IP Filters ☐ URL Blocking
☐ MAC Filters ☐ Domain Blocking

IP Filter

Use IP Filters to deny LAN IP addresses access to the Internet.

☐ Enabled ☐ Disabled

IP Address -

Port Range -

Protocol

Schedule ☐ Always

☐ From Time : To :
day to

Apply Cancel Help

IP Filter List

	IP Range	Protocol	Schedule	
<input type="checkbox"/>	*	TCP 20-21	always	
<input type="checkbox"/>	*	TCP 80	always	
<input type="checkbox"/>	*	TCP 443	always	
<input type="checkbox"/>	*	UDP 53	always	
<input type="checkbox"/>	*	TCP 25	always	
<input type="checkbox"/>	*	TCP 110	always	
<input type="checkbox"/>	*	TCP 23	always	

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home **Advanced** **Tools** **Status** **Help**

Filter

Filters are used to allow or deny LAN users from accessing the Internet.

- ☐ IP Filters ☒ URL Blocking
☐ MAC Filters ☐ Domain Blocking

URL Blocking

Block those URLs which contain keywords listed below.

- ☐ Enabled ☒ Disabled

- Empty -

DELETE

Apply Cancel Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home **Advanced** **Tools** **Status** **Help**

Filter

Filters are used to allow or deny LAN users from accessing the Internet.

- ☐ IP Filters ☐ URL Blocking
☒ MAC Filters ☐ Domain Blocking

MAC Filters

Use MAC address to allow or deny computers access to the network.

- ☒ Disabled MAC Filters
☐ Only **allow** computers with MAC address listed below to access the network
☐ Only **deny** computers with MAC address listed below to access the network

Name

MAC Address

DHCP Client

Apply Cancel Help

MAC Filter List

Name	MAC Address

Building Networks for People

High-Speed 2.4GHz Wireless Router

DI-724P+

- Virtual Server
- Application
- Filter**
- Firewall
- SNMP
- DDNS
- Routing
- DMZ
- Performance

Home **Advanced** Tools Status Help

Filter
Filters are used to allow or deny LAN users from accessing the Internet.

☐ IP Filters
 ☐ URL Blocking
 ☐ MAC Filters
 ☒ Domain Blocking

Domain Blocking

☒ Disabled
 ☐ Allow users to access all domains except "Blocked Domains".
 ☐ Deny users to access all domains except "Permitted Domains".

Permitted Domains

- Empty -

DELETE

Blocked Domains

- Empty -

DELETE

☒ Apply
 ☐ Cancel
 ☐ Help

Building Networks for People

High-Speed 2.4GHz Wireless Router

DI-724P+

- Virtual Server
- Application
- Filter
- Firewall**
- SNMP
- DDNS
- Routing
- DMZ
- Performance

Home **Advanced** Tools Status Help

Firewall Rules
Firewall Rules can be used to allow or deny traffic from passing through the DI-724P+.

☐ Enabled
 ☐ Disabled

Name

Action ☐ Allow ☐ Deny

Interface IP Start IP End Protocol Port Range

Source *

Destination * TCP

Schedule ☐ Always
 ☐ From Time : : To : : day to

☒ Apply
 ☐ Cancel
 ☐ Help

Firewall Rules List

Action Name	Source	Destination	Protocol
<input type="checkbox"/> Allow Allow to Ping WAN port	WAN,*	LAN,192.168.0.1	ICMP,*
<input type="checkbox"/> Deny Default	*,*	LAN,-192.168.0.1	*,*
<input type="checkbox"/> Allow Default	LAN,*	*,192.168.0.1	*,*

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home

Advanced

Tools

Status

Help

SNMP

Use Simple Network Management Protocol(SNMP) for DI-724P+ management purposes.

SNMP Local ☒ Enabled ☐ Disabled

SNMP Remote ☐ Enabled ☒ Disabled

Get Community

Set Community

IP 1

IP 2

IP 3

IP 4

SNMP Version ☐ V1 ☒ V2c



Apply



Cancel



Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home

Advanced

Tools

Status

Help

Dynamic DNS

Use Dynamic DNS if you want to use your DDNS account.

DDNS

☒ Disabled ☐ Enabled

Provider

DynDNS.org(Dynamic) ▼

Host Name

DynDNS.org(Dynamic)

DynDNS.org(Custom)

Username / E-mail

TZO.com

dhhs.org

Password / Key



Apply



Cancel



Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home

Advanced

Tools

Status

Help

Routing Table

Use the Routing Table for routing purposes within your local network.

ID	Destination	Subnet Mask	Gateway	Hop	Enable
1	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
2	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
3	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
4	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
5	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
6	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
7	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>
8	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>



Apply



Cancel



Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home

Advanced

Tools

Status

Help

DMZ

DMZ(Demilitarized Zone) is used to allow a single computer on the LAN to be exposed to the Internet.

☐ Enabled ☒ Disabled

IP Address 192.168.0.



Apply



Cancel



Help

DI-724P+



Virtual Server

Application

Filter

Firewall

SNMP

DDNS

Routing

DMZ

Performance

Home

Advanced

Tools

Status

Help

Wireless Performance

These are the Wireless Performance features for the AP(Access Point) portion.

Beacon Interval (msec, range:1~1000, default: 100)

DTIM Interval (range: 1~65535, default: 3)

TX Rates (Mbps)

Wireless Mode ☒ mixed mode ☐ G mode

Authentication Type ☐ Open System ☐ Shared Key ☒ Both

SSID broadcast ☒ Enable ☐ Disable

8X Mode ☒ Enable ☐ Disable



Apply



Cancel



Help

DI-724P+



Admin

Time

System

Firmware

Misc

Home

Advanced

Tools

Status

Help

Administrator Settings

Administrators can change their login password.

Administrator (The Login Name is "admin")

New Password

Reconfirm Password

User (The Login name is "user")

New Password

Reconfirm Password

Remote Management

Let administrator perform administration task from remote host.

☐ Enabled ☒ Disabled

IP Address 0.0.0.0

Port 8080



Apply



Cancel



Help

DI-724P+



Admin

Time

System

Firmware

Misc

Home

Advanced

Tools

Status

Help

Time

Set the DI-724P+ system time.

Device Time : Tue Nov 18 00:06:28 2003

☒ Enable NTP

Default NTP Server (Optional)

Time Zone

☐ Set Device Date and Time

Year: Month: Day:

Hour: Minute: Second:



Apply



Cancel



Help

DI-724P+



Admin

Time

System

Firmware

Misc

Home

Advanced

Tools

Status

Help

System Settings

Save Settings To Local Hard Drive

Backup Setting

Load Settings From Local Hard Drive

Browse...

Load

Restore To Factory Default Settings

Reset to Default



Help

DI-724P+



Admin

Time

System

Firmware

Misc

Home

Advanced

Tools

Status

Help

Firmware Upgrade

There may be new firmware for your DI-724P+ to improve functionality and performance. The upgrade procedure takes about 20 seconds. Note! Do not power off the unit when it is being upgraded. When the upgrade is done successfully, the unit will be restarted automatically.

Current Firmware Version: 1.00
Firmware Date: Tue, Nov 18 2003



Apply



Cancel



Help

[Admin](#)[Time](#)[System](#)[Firmware](#)[Misc](#)

Ping Test

Ping Test is used to send "Ping" packets to test if a computer is on the Internet.

Host Name or IP address

Restart Device

Reboots the DI-724P+.

Block WAN Ping

When you "Block WAN Ping", you are causing the public WAN IP address on the DI-724P+ to not respond to ping commands. Pinging public WAN IP addresses is a common method used by hackers to test whether your WAN IP address is valid.

Discard PING from WAN side ☐ Enabled ☒ Disabled

SPI mode

You can setup this item if you want to enable SPI mode.

☐ Enabled ☒ Disabled

UPnP Setting

You can disable or enable UPnP functions at anytime.

☒ Enabled ☐ Disabled

VPN Pass-Through

Allows VPN connections to work through the DI-724P+.

PPTP ☒ Enabled ☐ Disabled

IPSec ☒ Enabled ☐ Disabled

Non-standard FTP port

You have to setup this item if you want to access an FTP server whose port number is not 21.

Port:

DI-724P+



Device Info

Log

Stats

Wireless

Home

Advanced

Tools

Status

Help

Device Information

Firmware Version: 1.00, Tue, Nov 18 2003

LAN

MAC Address 00-0D-88-B0-E0-D5

IP Address 192.168.0.1

Subnet Mask 255.255.255.0

DHCP Server Enabled

WAN

MAC Address 00-0D-88-B0-E0-D4

Connection DHCP Client Disconnected.

Remaining Lease Time 00:00:00

IP Address 0.0.0.0

Subnet Mask 0.0.0.0

Gateway 0.0.0.0

Domain Name Server 0.0.0.0

Wireless

MAC Address 00-0D-88-B0-E0-D5

ESSID default

WEP Disable

Channel 6

Peripheral

Printer(DB25) Not ready

Device Time: Tue Nov 18 00:08:13 2003



Help

DI-724P+



Device Info

Log

Stats

Wireless

Home

Advanced

Tools

Status

Help

View Log

View Log displays the activities occurring on the DI-724P+. Click on Log Settings for advance features.

First Page

Last Page

Previous

Next

Clear

Log Settings



Page 1/6

WAN Type: Dynamic IP Address (1.00)

Display time: Tue Nov 18 00:08:35 2003

Monday, 17 November 2003 11:51:50 PM DOD:triggered internally
Monday, 17 November 2003 11:51:50 PM DHCP:discover()
Monday, 17 November 2003 11:51:54 PM DHCP:discover()
Monday, 17 November 2003 11:52:02 PM DHCP:discover()
Monday, 17 November 2003 11:52:18 PM DHCP:discover()
Monday, 17 November 2003 11:52:53 PM DOD:triggered internally
Monday, 17 November 2003 11:52:53 PM DHCP:discover()
Monday, 17 November 2003 11:52:57 PM DHCP:discover()
Monday, 17 November 2003 11:53:05 PM DHCP:discover()
Monday, 17 November 2003 11:53:21 PM DHCP:discover()

DI-724P+



Device Info

Log

Stats

Wireless

Home

Advanced

Tools

Status

Help

Log Settings

Logs can be saved by sending it to an admin email address or to a syslog server.

E-mail Alert

SMTP Server / IP Address

Email Address

Send Mail Now

E-mail Subject

Syslog

Syslog Server IP Address 192.168.0. ☐ Enabled ☒ Disabled

- Log Type
- ☒ System Activity
 - ☒ Debug Information
 - ☒ Attacks
 - ☒ Dropped Packets
 - ☒ Notice



Apply



Cancel



Help

DI-724P+



Device Info

Log

Stats

Wireless

Home

Advanced

Tools

Status

Help

Traffic Statistics

Traffic Statistics display Receive and Transmit packets passing through the DI-724P+.

Refresh

Reset



Help

	Receive	Transmit
WAN	0 Packets	41 Packets
LAN	1376 Packets	1375 Packets
Wireless	0 Packets	177 Packets

DI-724P+



Device Info

Log

Stats

Wireless

Home

Advanced

Tools

Status

Help

Connected Wireless Client List

The Wireless Client table below displays Wireless clients Connected to the AP (Access Point).

Refresh



Help

Connected Time

MAC Address

DI-724P+



Home

Advanced

Tools

Status

Help

Home

- [Setup Wizard](#)
- [Wireless](#)
- [WAN Settings](#)
- [LAN Settings](#)
- [DHCP Server](#)

Advanced

- [Virtual Server](#)
- [Special Applications](#)
- [Filters](#)
- [Firewall Rules](#)
- [SNMP](#)
- [DDNS](#)
- [Routing](#)
- [DMZ](#)
- [Wireless Performance](#)

Tools

- [Administrator Settings](#)
- [System Time](#)
- [System Settings](#)
- [Firmware Upgrade](#)
- [Miscellaneous Items](#)

Status

- [Device Information](#)
- [Log](#)
- [Traffic Statistics](#)
- [Wireless](#)

FAQs